

# 电动机 ELECTRIC MOTOR

## 200W、400W

● 平行轴减速机 Parallel shaft speed reducer

型号 Model number	电机型号 Motor type	减速机型号 Type of reducer	减速比 Deceleration ratio	L	L1
Z6BLD200-220GV-30S/6GU□V	Z6BLD200-220GV-30S	6GU□V	5 ~ 20	60	61.5
			30 ~ 50	72	
			100 ~ 200	86	
Z6BLD400-220GV-30S/6GU□V	Z6BLD400-220GV-30S	6GU□V	5 ~ 20	60	61.5
			30 ~ 50	72	

## S系列整机容许力矩 Machine allowable torque

● 平行轴减速机 Parallel shaft speed reducer

单位Unit: N·m

输出功率 Output power	电机轴转速 Motor speed	减速比 Reduction ratio	容许力矩 (N·m)							
			5	10	15	20	30	50	100	200
200W	80 ~ 2000RPM		2.9	5.7	8.6	11.5	16.4	27.4	51.6	70.0
	4000RPM		2.2	4.3	6.5	8.60	12.4	20.5	38.9	63.0
400W	80 ~ 3000RPM		5.7	11.4	17.1	22.9	32.8	54.6	-	-
	4000RPM		4.3	8.60	12.9	17.2	24.6	41.1	-	-

注Note: 表格中  (灰底部分) 表示旋转方向与电机转向一致。The  (gray) in the table indicates that the rotation direction is consistent with the motor. (不同转速及速比下的力矩为ZD标准驱动器下测试所得。The torque under different speed and speed ratio is obtained under the ZD standard)

## 外观尺寸图 Dimensional drawing

